

IMPORTANT SAFETY INSTRUCTIONS

1. These instructions are provided for your safety. It is important that they are read carefully and completely before installing the chandelier.

2. THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH APPLICABLE INSTALLATION CODES BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HARZARDS INVOLVED.

We strongly recommend that an authorized and certified electrician install all direct wire fixtures

3. This fixture has been rated from 6 x 40watt Max E12 standard bulb(not included).

4. To avoid the risk of fire, do not exceed the recommended wattage.

The light fixture is meant for indoor use. DRY LOCATION ONLY. It must be connected only to 3-wire. Single-phase electrical systems (provided with Ground wire or equivalent protection system).

5. Keep it away from children.

WARNING:

. Turn-off electricity supply at main circuit panel before installing. Do not connect electricity supply until your chandelier is fully assembled and installed.

. To reduce the risk of fire, electrical shock, or personal injury, always turn off the chandelier and allow it to cool Prior to replacing light bulb. Do not touch bulb when fixture is turned on or look directly at light bulb.

. Keep flammable materials away from light bulb.

PRE-ASSEMBLY:

. Remove all parts and hardware from box along with plastic protective packaging. Do not discard any contents until after assembly is complete to avoid accidentally discarding small parts or hardware.

. For your safety and convenience, assembly by two people is recommended

INSTALLATION:

1. Carefully remove all parts from the box. Place them on a clean, soft surface.

2. Remove mounting plate (b) from canopy (d).

3. Install mounting plate (b) to the junction box and secure with mounting screws (c).

4. Cut excess wires, being sure to leave enough length to reach the junction box. Separate wires and strip 5/8" of insulation from each wire.

5. Gently pull the wiring from the outlet box and allow the wires to hang. Carefully inspect the fixture's wires. The NEUTRAL FIXTURE WIRE is marked with "N". The HOT FIXTURE WIRE is marked with "L". The unmarked GREEN wire is the GROUND WIRE.

6. Connect the GROUND WIRE from the fixture to the GROUND JUNCTION BOX WIRE from the outlet (usually green or bare wire) using wire connector (a).

7. NOTE: It is imperative that the fixture is grounded.

8. Connect the fixture neutral wire (white) to the supply neutral wire (usually white) using wire nut (a).

9. Connect the fixture hot wire (black) to the supply hot wire (usually black) using wire connector (a). CAUTION: Do not reverse the hot and neutral connections.

10. Make sure all wire connections are tight, then carefully tuck them into the junction box.

11. Unlock link loop (e) and attach to the collar loop (f).

Move the canopy (d) up to the ceiling, and affix it with the ring knob on the chain. Ensure that it is the chain and not the power cord that is supporting the fixture's weight.

12. Install light bulbs (g) into the sockets.

PARTS ENCLOSED:

- (a) Wire Connectors (3)
- (b) Mounting Bar (1)
- (c) Mounting screw (3)
- (d) Canopy (1)
- (e) Chain (1)
- (f) Fixture (1)
- (g) Bulbs (6)

TOOLS REQUIRED (Not Included)

- Philips screwdriver, Slotted Screwdriver
- Wire Strippers
- Slip Joint Pliers, Measuring Tape, Chain Pliers
- Wire cutters

Breakdown Diagram 1:

